

ORDERING INFORMATION

Model : MXF

PLEASE FILL IN THIS SECTION



Model
Company
Name
P/O No.

FACTORY USE ONLY



Job No.	Approved by (Sales office)
Ser No.	Issued by (Sales office)
Sales	Approved by (Factory)
	Set by (Factory)

Specify the items you want to change. Default setting will be used if not specified.

DEFAULT shows values in case of nothing specified.

SOFTWARE SETTING

ITEM	DATA	CONTENTS	DEFAULT VALUE	SPECIFY YOUR PREFERENCE	Factory Internal check
09	0, 1, 2, 3	Function 0 : Proportional $F(X) = X$ 1 : Square $F(X) = X^2$ 2 : Reciprocal $F(X) = 1/100X$ 3 : Square root $F(X) = \sqrt{X} *_1$	0		<input type="checkbox"/>
10	-99.99 – 99.99	Output bias (%)	0.00		<input type="checkbox"/>
11	0.000 – 9.999	Output gain	1.000		<input type="checkbox"/>
12	-15.0 – 115.0	Output low limit (%) (ITEM 12 < ITEM 13)	-15.0		<input type="checkbox"/>
13	-15.0 – 115.0	Output high limit (%) (ITEM 12 < ITEM 13)	115.0		<input type="checkbox"/>
14	-9999 – 9999	Display range scaling 0% * ₂	0.0		<input type="checkbox"/>
15	-9999 – 9999	Display range scaling 100% * ₂	100.0		<input type="checkbox"/>
16	0, 1, 2, 3	Decimal point position 0 : ____ 1 : ____. 2 : ____. 3 : ____.	1		<input type="checkbox"/>
17	0, 1, 2, 3, 4	Moving average (sampling cycle: 10 msec.) 0: No 1: 4 samples 2: 8 samples 3: 16 samples 4: 32 samples	0		<input type="checkbox"/>
18	0, 1 – 60	Power-saving mode 0 : Continuous display 1 – 60 : Time before display turned off (minutes)	10		<input type="checkbox"/>
19	-1.00 – 1.00 -10.0 – 10.0 -30.0 – 30.0	Input code S1 Input code S2 Input code S3	0% input voltage (V) * ₃ 0% input voltage (V) * ₃ 0% input voltage (V) * ₃	S1: -1.00 S2: -10.0 S3: -30.0	<input type="checkbox"/>
20	-1.00 – 1.00 -10.0 – 10.0 -30.0 – 30.0	Input code S1 Input code S2 Input code S3	100% input voltage (V) * ₃ 100% input voltage (V) * ₃ 100% input voltage (V) * ₃	S1: 1.00 S2: 10.0 S3: 30.0	<input type="checkbox"/>
21	-1.00 – 1.00 -10.0 – 10.0 0.0 – 20.0	Output code V1 Output code V2 Output code Z1	0% output voltage (V) * ₄ 0% output voltage (V) * ₄ 0% output current (mA) * ₄	V1: -1.00 V2: -10.0 Z1: 4.0	<input type="checkbox"/>
22	-1.00 – 1.00 -10.0 – 10.0 0.0 – 20.0	Output code V1 Output code V2 Output code Z1	100% output voltage (V) * ₄ 100% output voltage (V) * ₄ 100% output current (mA) * ₄	V1: 1.00 V2: 10.0 Z1: 20.0	<input type="checkbox"/>
23	0, 1	Output characteristics 0 : Positive 1 : Negative (inverted output)	0		<input type="checkbox"/>

*1 : The calculated result with the input ≤ 0.001 is rounded to 0.

*2 : Of the range set in ITEM 19/20. ITEM 14 < ITEM 15.

*3 : ITEM 19 < ITEM 20.

*4 : ITEM 21 < ITEM 22.

*5 : Press DATA UP key and choose DATA 1. Double-click DATA DOWN key. The display shows DATA 0 after the initialization is complete.