

## Bargraph Indicators 48N Series


(See 'External View.')

### BARGRAPH INDICATING ALARM

(thermocouple input)

#### Functions & Features

- Displays a process variable in graphic bargraph of 101 LED segments
- Provides max. 4 alarm contact outputs
- Multi-color indicator
- Linearization and burnout
- IP65 front cover
- Scale plate is easily replaced
- Separable terminal block



### [3] MOUNTING DIRECTION

V: Vertical

H: Horizontal

### [4] INPUT THERMOCOUPLE

1: (PR) (Usable Range 0 to 1760°C, 32 to 3200°F)

2: K (CA) (Usable range -270 to +1370°C, -454 to +2498°F)

3: E (CRC) (Usable range -270 to +1000°C, -454 to +1832°F)

4: J (IC) (Usable range -210 to +1200°C, -346 to +2192°F)

5: T (CC) (Usable range -270 to +400°C, -454 to +752°F)

6: B (RH) (Usable range 0 to 1820°C, 32 to 3308°F)

7: R (Usable range -50 to +1760°C, -58 to +3200°F)

8: S (Usable range -50 to +1760°C, -58 to +3200°F)

N: N (Usable range -270 to +1300°C, -454 to +2372°F)

### [5] POWER INPUT

AC Power

M: 85 - 264 V AC (Operational voltage range 85 - 264 V, 50/60 Hz (CE or UKCA marking not available))

M2: 100 - 240 V AC (Operational voltage range 85 - 264 V, 50/60 Hz)

DC Power

R: 24 V DC

(Operational voltage range 24 V ±15 %, ripple 10 %p-p max.)

## MODEL: 48NAT-[1][2][3][4]-[5][6]

### ORDERING INFORMATION

- Code number: 48NAT-[1][2][3][4]-[5][6]
- Specify a code from below for each of [1] through [6]. (e.g. 48NAT-42V2-R/CE/D/BL/Q)
- Temperature range (e.g. 0 - 500 °C)
- Bargraph scale (e.g. 0 - 100 %) (See 'Scale Plate.')
- Specify the specification for option code /Q (e.g. /C01/SET)

### [1] ALARM OUTPUT

2: 2 points

4: 4 points

### [2] BAR LED COLOR

R: Red

Y: Amber

G: Green

B: Blue

1: Multi-color (red, orange and green), Pattern 1 (See 'External View.')

2: Multi-color (red, orange and green), Pattern 2

### [6] OPTIONS (multiple selections)

Standards & Approvals

blank: Without CE

/CE: CE marking

/UK: CE, UKCA marking

Bezels

blank: Bezels for the 48 Series panel cutout

/D: Bezels for DIN panel cutout

/F: Bezels for Fuji Electric's PAJ, PAK, PBA panel cutout

Burnout

blank: Upscale burnout

/BL: Downscale burnout

/BN: No burnout

Other Options

blank: none

/Q: Option other than the above (specify the specification)

### SPECIFICATIONS OF OPTION: Q (multiple selections)

COATING (For the detail, refer to our web site.)

Moving parts and indicators are not coated.

/C01: Silicone coating

/C02: Polyurethane coating

/C03: Rubber coating

EX-FACTORY SETTING

/SET: Preset according to the Ordering Information Sheet (No. ESU-9437)

## BEZEL OPTION

Bezels are used to adapt the 48N Series to an existing panel cutout. In order to replace the 48 Series products, use the one attached to the 48N Series as standard. When the existing panel is cut according to DIN standard, specify '/D' suffix code.

For a new installation, no bezel is required. Please refer to 'Mounting Requirement' and mount the 48N directly. Ingress protection is invalid when the 48N is mounted with a bezel, or when multiple modules are stacked side by side.

## SPARE PARTS

- Scale plate

## GENERAL SPECIFICATIONS

**Construction:** Panel flush mounting

**Degree of protection:** IP65; applicable to the front panel for single unit mounted according to the specified panel cutout

**Connection:** M3 separable screw terminal (torque 0.6 N·m)

**Screw terminal:** Nickel-plated steel

**Housing material:** Flame-resistant resin (black)

**Isolation:** Input to output to power

**Zero adjustment:** 0 - 10 % (front)

**Span adjustment:** 90 to 100 % (front)

**Scale plate:** Flame resistant resin (white scale & characters on black base)

**Setpoint adjustment**

**2 points:**

H [L setpoint ] to 100 %

L 0 to [H setpoint]

or No alarm trip

**4 points:**

HH [H setpoint] to 100 %

H [L setpoint] to [HH setpoint]

L [LL setpoint] to [H setpoint]

LL 0 to [L setpoint]

or No alarm trip

**Alarm deadband (hysteresis):** 1 %

**Burnout:** Upscale standard; downscale or no burnout optional.

The highest bargraph segment blinks with upscale burnout; the lowest blinks with downscale burnout.

**Linearization:** Standard

**Cold junction compensation:** CJC sensor attached to the input terminals (B thermocouple is without CJC as standard)

**Setting:** (Front button)

- Zero and span adjustments
- Alarm setpoint

- Others

(Refer to the instruction manual for details)

### ■ BARGRAPH

**LED:** 101-segment LED, 100 mm (3.96") long, 3.00 mm (.12") wide

**Display range:** 0 to 100 (scaling function not available)

**Scale:** Two different scales available for single bargraph

**Characters:** Max. 4 characters including decimal point and negative sign

**Divisions:** Min. 22, max. 100

**Engineering unit:** Max. 6 characters

## INPUT SPECIFICATIONS

■ **Input:** Thermocouples

**Minimum span:** 3 mV

**Input resistance:**  $\geq 20$  k $\Omega$

**Burnout sensing:**  $\leq 0.25$   $\mu$ A

**Temperature range (in °C)**

**(PR):** min. span 370°C; lower range 0 to 880°C

**K (CA):** min. span 75°C; lower rang -270 to +1200°C

**E (CRC):** min. span 50°C; lower range -270 to +750°C

**J (IC):** min. span 60°C; lower range -210 to +800°C

**T (CC):** min. span 75°C; lower range -270 to +325°C

**B (RH):** min. span 780°C; lower range 0 to 750°C

**R:** min. span 360°C; -50 to +550°C

**S:** min. span 380°C; -50 to +550°C

**N:** min. span 110°C; -270 to +1100°C

**Temperature range (in °F)**

**(PR):** min. span 670°F; lower range 32 to 1616°F

**K (CA):** min. span 140°F; lower range -454 to +2192°F

**E (CRC):** min. span 90°F; -454 to +1382°F

**J (IC):** min. span 110°F; -346 to +1472°F

**T (CC):** min. span 140°F; -454 to +617°F

**B (RH):** min. span 1450°F; 32 to 1382°F

**R:** min. span 680°F; -58 to +1022°F

**S:** min. span 700°F; -58 to +1022°F

**N:** min. span 200°F; -454 to +2012°F

Note: The transmitter may not satisfy specified accuracy for temperature ranges below 0°C. For more details, consult us.

## OUTPUT SPECIFICATIONS

■ **Alarm Output:** Relay contact

**Rated load:** 250 V AC @1 A ( $\cos \theta = 1$ )

30 V DC @5 A (resistive load)

**Maximum switching voltage:** 250 V AC, 220 V DC

**Maximum switching power:** 380 VA, 150 W


**Minimum load:** 5 V DC @100 mA

**Mechanical life:**  $\geq 5 \times 10^8$  cycles (rate 180 cycles/min.)


## Alarm Trip Operation

Terminal No. in parentheses

### • Alarm Output Code 2



### • Alarm Output Code 4



**Temp. coefficient:**  $\pm 0.015$  % of FS/ $^{\circ}$ C ( $\pm 0.008$  % of FS/ $^{\circ}$ F)  
(at over  $400^{\circ}$ C or  $750^{\circ}$ F for R, S and PR; over  $770^{\circ}$ C or  $1420^{\circ}$ F for B)

**Response time:**  $\leq 0.5$  sec.

**Burnout response:**  $\leq 10$  sec.

**Insulation resistance:**  $\geq 100$  M $\Omega$  with 500 V DC

**Dielectric strength:** 2000 V AC @1 minute (input to output to power to ground)

## STANDARDS & APPROVALS

### EU conformity:

EMC Directive

EMI EN 61000-6-4

EMS EN 61000-6-2

Low Voltage Directive

EN 61010-1

Measurement Category II (output)

Installation Category II (power)

Pollution Degree 2

Input to output to power: Reinforced insulation (300 V)

RoHS Directive

### UK conformity (UKCA):

The UK legislations and designated standards are equivalent to the applicable EU directives.

(Refer to our website for more information about the legislations and designated standards.)

## INSTALLATION

### Power Consumption

#### •AC:

Approx. 5.5 VA at 100 V with max. load

Approx. 7 VA at 200 V with max. load

Approx. 8 VA at 264 V with max. load

#### •DC

Approx. 3.5 W at 20.4 V with max. load

Approx. 3.5 W at 24 V with max. load

Approx. 3.5 W at 27.6 V with max. load

**Operating temperature:**  $-5$  to  $+55^{\circ}$ C (23 to  $131^{\circ}$ F)

**Operating humidity:** 30 to 90 %RH (non-condensing)

**Mounting:** Panel flush mounting

**Weight:** 300 g (0.66 lb)

## PERFORMANCE in percentage of span

### Accuracy

**Bargraph (LED), alarm output:**  $\pm 1$  %  $\pm 1$  digit

(at over  $400^{\circ}$ C or  $750^{\circ}$ F for R, S and PR; over  $770^{\circ}$ C or  $1420^{\circ}$ F for B)

### Cold junction compensation error

(at  $20^{\circ}$ C  $\pm 10^{\circ}$ C or  $68^{\circ}$ F  $\pm 18^{\circ}$ F)

**K, E, J, T, N:**  $\pm 0.5^{\circ}$ C or  $\pm 0.9^{\circ}$ F

**S, R, PR:**  $\pm 1^{\circ}$ C or  $\pm 1.8^{\circ}$ F

**SCALE PLATE**

**■ WHAT MUST BE SPECIFIED WHEN ORDERING**

Following two methods can specify scale plate.

**a) Using 'Scale Plate Designer'**

Access 'Design Scale Plate' in the our web site. Scale plate can be designed in this web site.

By function below, it can be easy to create standard design or original design.

**[Design Automatically]**

Entering Minimum, Maximum, and Unit allows to create automatically a scale plate.

Maximum created scale division number is '54.9'. Use [Specify Division Number], if division number more than '54.9' is required (Maximum 100 division).

**[Specify Division Interval]**

Division Interval can be specified according to the application.

**[Specify Division Number]**

It is available to create originally with scale division number, length of line, position, character size, font and detailed position.

After designing is completed, register code is issued. Place the order with this code.

Once scale plate is designed, it is recorded. The register code can be used any number of times.

**b) Specifying scale range and display unit when placing the order**

It is available to create by specifying scale range and display unit for right and left.

Regarding design of scale plate such as division number, length of division number line, and character font, they are same as above [Design Automatically], we design them.

**■ DESIGNING BY 'DESIGN AUTOMATICALLY'**

How 'Design Automatically' creates scale design is described succinctly below.

**■ TYPES OF DIVISIONS**

Five (5) types of divisions are used depending upon the scale span, which determined by the following equation:

$$\text{Scale Span} = (\text{Max. range value} - \text{Min. range value}) \times 10$$

where n = integer (used to limit the calculated scale span to the minimum of 1.1, below 11.0.)

The number of divisions is automatically determined by the scale span.

**• Type 1: 1.1 Scale Span < 1.3**

Number of divisions: 22 to 25.9

Scale: Starts at 0, increments by 0.02 / 0.2 / 2 / 20 /

200. Min. and max. values indicated. 4 digits including negative sign and decimal point.

Division lines: Long, Short, Medium, Short, Long (4 divisions repeated)

**• Type 2: 1.3 Scale Span < 2.0**

Number of divisions: 26 to 39.9

Scale: Starts at 0, increments by 0.03 / 0.3 / 3 / 30 /

300. Min. and max. values indicated. 4 digits including negative sign and decimal point.

Division lines: Long, Short, Medium, Short, Medium, Short, Long (6 divisions repeated)

Minimum Divisions	Maximum Divisions	Bipolar Scale
11	1.29	600
10	1.2	400
8	1.0	200
6	0.8	0
4	0.6	-200
2	0.4	-400
0	0.2	-600


Minimum Divisions	Maximum Divisions	Bipolar Scale
130	1.99	0.8
120	1.8	0.6
90	1.5	0.3
60	1.2	0
30	0.9	-0.3
0	0.6	-0.6
0	0.3	-0.8

• **Type 3: 2.0 Scale Span < 2.6**

Number of divisions: 40 to 51.9

Scale: Starts at 0, increments by 0.05 / 0.5 / 5 / 50 / 500. Min. and max. values indicated. 4 digits including negative sign and decimal point.

Division lines: Long, Short, Medium, Short, Medium, Short, Medium, Short, Medium, Short, Long (10 divisions repeated)




• **Type 5: 5.5 Scale Span < 11.0**

Number of divisions: 27.5 to 54.9

Scale: Starts at 0, increments by 0.01 / 0.1 / 1 / 10 / 100 / 1000. Min. and max. values indicated. 4 digits including negative sign and decimal point.

Division lines: Long, Medium, Medium, Medium, Medium, Long (5 divisions repeated)



• **Type 4: 2.6 Scale Span < 5.5**

Number of divisions: 26 to 54.9

Scale: Starts at 0, increments by 0.05 / 0.5 / 5 / 50 / 500. Min. and max. values indicated. 4 digits including negative sign and decimal point.

Division lines: Long, Medium, Medium, Medium, Medium, Long (5 divisions repeated)



[Example] : Bargraph range 0 to 300°C (Type 4) for left  
Bargraph range 0 to 100 % (Type 5) for right

Left scale range: 0 – 300

Left scale unit (bargraph): °C

Right scale range: 0 – 100


Right scale unit (bargraph): %




## EXTERNAL VIEW

### ■ ALARM OUTPUT CODE 2: 2 points

#### • Vertical Mounting




#### • Horizontal Mounting




### ■ ALARM OUTPUT CODE 4: 4 points

#### • Vertical Mounting




#### • Horizontal Mounting




### • Bar Color Patterns


#### Pattern 1 (Bar LED color code 1)



#### Pattern 2 (Bar LED color code 2)




## EXTERNAL DIMENSIONS & TERMINAL ASSIGNMENTS unit: mm [inch]



### ■ STANDARD BEZEL \*2

### ■ OPTION /D BEZEL \*3

### ■ OPTION /F BEZEL \*4




- \*1. Space required when replacing the scale plate.
- \*2. Used for the existing panel cutout of the 48 Series (38 × 139.5 mm).
- \*3. Used for the existing DIN panel cutout (33 × 138 mm)
- \*4. Used for the existing panel cutout of Fuji Electric PAJ, PAK, PBA (44 × 138 mm), etc.

## PANEL CUTOUT unit: mm


### ■ SINGLE MOUNTING (Conform to degree of protection IP65)

#### • Vertical Mounting



Panel thickness: 1.6 – 8.0 mm


#### • Horizontal Mounting



Panel thickness: 1.6 – 8.0 mm

### ■ CLUSTERED MOUNTING (Not conform to degree of protection IP65)

#### • Vertical Mounting




Panel thickness: 1.6 – 8.0 mm

$$L = \{31.5 + 36 \times (N - 1)\} +1/-0$$

(N : number of units)

#### • Horizontal Mounting



Panel thickness: 1.6 – 8.0 mm

$$L = \{31.5 + 36 \times (N - 1)\} +1/-0$$


(N : number of units)

Note 1: Observe at the minimum of 3 cm above and below the units for heat dissipation.  
 Note 2: No bezel is needed when the panel is cut according to the above drawings.




## SCHEMATIC CIRCUITRY & CONNECTION DIAGRAM

### ■ ALARM OUTPUT CODE 2: 2 points




### ■ ALARM OUTPUT CODE 4: 4 points




#### ■ Relay Protection

- AC Powered



- DC Powered



Specifications are subject to change without notice.