# **Super-mini Signal Conditioners Mini-M Series**

## **CURRENT LOOP SUPPLY**


(non-isolated)

#### **Functions & Features**

- Powers a 4 20 mA DC current loop
- Electrically isolating output signal from power input
- Shortcircuit protection
- Applicable to smart transmitters

### **Typical Applications**

• Various 2-wire transmitters



MODEL: M2D-24-[1][2]

#### ORDERING INFORMATION

• Code number: M2D-24-[1][2]

Specify a code from below for each of [1] and [2].

(e.g. M2D-24-R/CE/Q)

 $\bullet$  Specify the specification for option code /Q

(e.g. /C01/S01)

### **SUPPLY OUTPUT**

24: 24 V DC

#### INPUT

Current

4 – 20 mA DC (Input resistance 250  $\Omega$ )

#### **OUTPUT 1**

Voltage

1 – 5 V DC (Load resistance 250  $k\Omega$  min.)

## **OUTPUT 2**

Current

4 - 20 mA DC

## [1] POWER INPUT

AC Power

M: 85 - 264 V AC (Operational voltage range 85 - 264 V,

47 - 66 Hz)

(Select '/N' for 'Standards & Approvals' code.)

DC Power

R: 24 V DC

(Operational voltage range 24 V ±10 %, ripple 10 %p-p max.)

**R2**: 11 - 27 V DC

(Operational voltage range 11 – 27 V, ripple 10 %p-p max.)

(Select '/N' for 'Standards & Approvals' code.)

P: 110 V DC

(Operational voltage range 85 - 150 V, ripple 10 %p-p max.)

(Select '/N' for 'Standards & Approvals' code.)

# [2] OPTIONS (multiple selections)

Standards & Approvals (must be specified)

/N: Without CE, UKCA or UL

/CE: CE marking /UK: CE, UKCA marking

/UL: UL approval, CE marking

Other Options **blank**: none

/Q: Option other than the above (specify the specification)

### **SPECIFICATIONS OF OPTION: Q (multiple selections)**

COATING (For the detail, refer to our web site.)

/C01: Silicone coating /C02: Polyurethane coating

/C03: Rubber coating (UL not available)
/C04: Polyolefin coating (UL not available)

TERMINAL SCREW MATERIAL

/S01: Stainless steel (UL not available)

## **GENERAL SPECIFICATIONS**

Construction: Plug-in

**Connection**: M3 screw terminals (torque 0.8 N·m) **Screw terminal**: Chromated steel (standard) or stainless

steel

Housing material: Flame-resistant resin (black)

Isolation: Input or output to power

### **SUPPLY OUTPUT**

Output voltage: 24 - 28 V DC with no load

Current rating: ≤ 22 mA DC
• Shortcircuit Protection
Current limited: 35 mA max.
Protected time duration: No limit

## **INPUT SPECIFICATIONS**

■ DC Current: Input resistor incorporated

## **INSTALLATION**

### **Power Consumption**

•AC:

Approx. 3 VA at 100 V Approx. 4 VA at 200 V Approx. 5 VA at 264 V •DC: Approx. 3 W

Operating temperature: -5 to +55°C (23 to 131°F)
Operating humidity: 30 to 90 %RH (non-condensing)

**Mounting**: Surface or DIN rail **Weight**: 150 g (0.33 lb)

## **PERFORMANCE** in percentage of span

Accuracy:  $\pm 0.1$  % (accuracy of the receiving resistor) Temp. coefficient:  $\pm 0.003$  %/°C ( $\pm 0.002$  %/°F) (temp.

coefficient of the receiving resistor)

Line voltage effect to supply output: ±3 % over voltage

range

Insulation resistance:  $\geq 100 \text{ M}\Omega$  with 500 V DC

Dielectric strength: 2000 V AC @1 minute (input or output

to power to ground)

## **STANDARDS & APPROVALS**

## EU conformity:

**EMC** Directive

EMI EN 61000-6-4

EMS EN 61000-6-2

**RoHS** Directive

### UK conformity (UKCA):

The UK legislations and designated standards are equivalent to the applicable EU directives.

(Refer to our website for more information about the legislations and designated standards.)

#### Approval:

UL/C-UL nonincendive Class I, Division 2,


Groups A, B, C, and D

(ANSI/ISA-12.12.01, CAN/CSA-C22.2 No.213)

UL/C-UL general safety requirements


(UL 61010-1, CAN/CSA-C22.2 No.61010-1)

# **EXTERNAL DIMENSIONS** unit: mm [inch]




• When mounting, no extra space is needed between units.

## **TERMINAL ASSIGNMENTS**



# **SCHEMATIC CIRCUITRY & CONNECTION DIAGRAM**



<sup>\*</sup> Short across these terminals for large voltage allowance at Output 2. Be sure to match specifications of smart transmitter. Do not connect a capacitive load to Output 1.

<sup>\*\*</sup>Short across these terminals when not using output 2.

⚠ Specifications are subject to change without notice.